

"Express Mail" mailing label number 4 EL392682629US

Date of Deposit: January 17, 2001



Our Case No. 10506/3

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE  
APPLICATION FOR UNITED STATES LETTERS PATENT

INVENTOR:

Manouchehr S. Rafie  
Tushar Shah  
Syang-Myau Hwang  
Jun Lu

TITLE:

CARRIER PHASE RECOVERY  
SYSTEM FOR ADAPTIVE BURST  
MODEMS AND LINK HOPPING  
RADIO NETWORKS

ATTORNEY:

John G. Rauch  
Reg. No. 37,218  
BRINKS HOFER GILSON & LIONE  
P.O. BOX 10395  
CHICAGO, ILLINOIS 60610  
(312) 321-4200

## CARRIER PHASE RECOVERY SYSTEM FOR ADAPTIVE BURST MODEMS AND LINK HOPPING RADIO NETWORKS

### BACKGROUND

5        This invention relates to a carrier phase recovery subsystem employed in  
fixed Broadband Wireless Access (BWA) applications operating in adaptive burst  
modems and multi-link hopping mesh radio networks over slow time-varying  
channels. The adaptive modem is capable of fast link-hopping from one link to  
another over such channels. That is the channel is quasi-static from burst to burst  
for any given link.

10        The embodiments described herein may be used in conjunction with a  
wireless mesh topology network of the type described in US Patent Application  
serial number 09/187,665, entitled "Broadband Wireless Mesh Topology  
Networks" and filed November 5, 1998 in the names of J. Berger and I. Aaronson,  
and with network nodes including switched multi-beam antenna designs similar to  
15        the design described in US Patent Application serial number 09/433,542, entitled  
"Spatially Switched Router for Wireless Data Packets" and filed in the names of J.  
Berger, et al., as well as with the method and apparatus disclosed in U.S. Patent  
Application serial number 09/699,582 entitled "Join Process Method For  
Admitting A Node To A Wireless Mesh Network, filed October 30, 2000 in the  
20        names of Y. Kagan, et al. Each of these U.S. patent applications is incorporated  
herein by reference.

25        \* Burst transmission of digital data is employed in several applications such  
as satellite time-division multiple access, digital cellular radio, wideband mobile  
systems and broadband wireless access systems. The design trade-offs and the  
resulting architectures are different in each of these applications.

30        \* In most of these applications, a preamble of known symbols is inserted in  
the beginning of each burst of data packets for synchronization purposes. Data-  
aided (DA) algorithms are normally employed for good performance for short  
preamble. However, synchronization becomes difficult at low values of signal-to-  
noise ratio (SNR).

Coherent detection schemes are superior compared to differential coherent or non-coherent schemes in terms of power efficiency. However, carrier phase recovery required for coherent detection is influenced by a time-varying characteristic of a fading channel. The power efficiency presented by coherent detection in a digital communication system is effective only if carrier phase synchronization techniques are provided for the receiver.

A constant need for ever-increasing throughputs through fixed bandwidths, fueled by broadband IP (Internet protocol) applications, has pushed system designers toward more throughput-efficient modulation schemes. Because of their relatively good performance, large quadrature amplitude modulation (QAM) constellations are being used in many of these applications. One of the critical problems associated with the use of large QAM constellations is that of carrier phase estimation, which for efficiency reasons, must often be done without the use of a preamble, particularly in burst modem applications. The problem is further complicated for cross-talk interference between the quadrature components (i.e., I/Q channels).

For coherent detection, there are two basic approaches to establish carrier phase synchronization at the receiver. One is pilot based where a known signal is inserted at the transmitter that allows the receiver to extract the pilot symbol and synchronize its local oscillator to the carrier phase of the received signal. Known symbols are multiplexed with the data sequence in a ratio of  $p$  pilots to  $m$  data symbols. At the receiver, the incoming waveform is filtered and sampled at the symbol rate. The sample sequence is split into two streams; a data stream and a reference stream of known symbols. The latter is decimated and only the samples corresponding to pilot symbols are used for further processing. A narrow band phase-locked loop (PLL) is typically employed to acquire and track the carrier component of the received signal.

Such an approach is not appropriate in applications involving transmission of short bursts. The insertion of a known data sequence greatly reduces the

transmission efficiency for a short burst. As a result, pilot-aided algorithms are not applicable in such systems.

In the second approach, the carrier phase estimate is derived directly from the modulated signal. This approach is much more prevalent in practice due to its distinct advantage that the total transmitter power is allocated to the transmission of the data symbols. Transmission efficiency is optimized.

The effect of carrier phase error,  $\phi_e = \phi - \hat{\phi}$ , in high-level modulation schemes, such as M-QAM is to reduce the power of the desired signal component by a factor of  $\cos^2(\phi - \hat{\phi})$  in addition to the cross-talk interference from the in-phase and quadrature components. Since the average power level of the in-phase and quadrature components is the same, a small phase error causes a large degradation in performance, particularly at higher modulation levels (i.e.,  $M \geq 16$ ).

In continuous modem applications, the user is typically willing to wait a few seconds while the receiver goes through an acquisition phase in which tracking processes converge. Often, the acquisition process in a continuous modem simply allows phase-locked loops to pull in on the received signal. In other words, the acquisition processing is not different from the tracking processing.

In contrast, in a burst modem, the user data content of a given transmission may be only a fraction of a millisecond. Long acquisition times contribute an unacceptable level of overhead to the system and substantially reduce capacity. Thus, the burst modem requires a special acquisition process that will quickly estimate the appropriate receiver gain, the carrier frequency and phase, the sample timing frequency and phase, and, if needed, the equalizer taps for an equalizer of the receiver. Also, the acquisition process must reliably identify which bit in the burst is the first user data bit so that higher layers of the protocol stack can format data properly.

The initial carrier phase can be estimated using the phase of the output of a coherent correlator. This phase is an estimate of the phase of a sample in the

middle of the preamble. If we desire estimates of the phase at the beginning or the end of the preamble, the estimate from the middle must be compensated by the frequency error estimate. Since the frequency error estimate is not perfectly accurate, use of it for this compensation will degrade the accuracy of the phase estimate formed for the preamble ends. Thus, it should be carefully considered whether to start tracking from either end of the preamble or whether starting in the middle is the best route.

Another important design decision is the choice of the estimator topology. In continuous modem applications, closed-loop (feedback) structure is commonly used with relatively high performance depending on the application. However in burst modem systems, closed-loop structures do not produce the best results. Feedback systems require, in general, longer tracking time (i.e., long data sequence) for an acceptable performance level in many applications. This requirement is typically not met in burst modems where the burst length could be in the low microseconds (i.e., 20 to 40 octets).

Accordingly, there is a need for a method and apparatus for carrier phase recovery in a burst mode system. Further, there is a need for a method and apparatus for carrier phase recovery in a link hopping system using transmission bursts for radio communication.

## BRIEF SUMMARY

By way of introduction only, the present invention provides a method for receiving radio signals in a multiple-link hopping radio system. The method includes hopping among a plurality of radio links to receive bursts of radio signals on the plurality of radio links and determining channel information for each radio link from a received burst on the radio link. Further, the method includes storing the determined channel information and using the determined channel information for the radio link to reliably receive a next received burst on the radio link.

The invention further provides a method for receiving radio signals which includes receiving a first burst of a first radio signal on a first radio link and determining channel information about the first radio link using the first burst.

The method further includes receiving a next burst such as a second burst of the first radio signal or a first burst of a second radio signal on a second radio link and, subsequently, receiving a next burst of the first radio signal on the first radio link using the channel information.

5           The invention further provides a carrier phase recovery method for use in a multiple-link hopping, burst adaptive modem. The method includes receiving a modulated carrier signal as a series of bursts, each burst including one or more pilot symbols and data symbols and forming a coarse estimation of carrier phase using the one or more pilot symbols. Further, the method includes forming a fine  
10           estimation of carrier phase using the coarse estimation of carrier phase to estimate carrier phase for a burst using data symbols of the burst, and correcting carrier phase for the radio signal using the fine estimation of carrier phase.

          The invention further provides carrier phase recovery system. The system includes a fixed equalizer configured to equalize a present burst of data using  
15           equalizer weights from a previous burst of data generated by an adaptive equalizer. The present burst of data includes pilot symbols and data. The system further includes a carrier phase recovery unit which recovers phase for the present burst of data using the pilot symbols and a mixer combining a delayed present burst of data and the recovered phase. The system still further includes an  
20           adaptive equalizer which equalizes the present burst to produce an equalized output signal and provides next burst equalizer weights to a fixed equalizer for equalizing a next burst of data.

          The invention further provides a phase correction apparatus which includes  
25           in one embodiment means for receiving a distorted signal and means for compensating for the phase of the distorted signal. The compensating means includes means using known pilot symbols in the distorted signal for obtaining a coarse estimate of carrier phase for the distorted signal, and means using data symbols of the coarse phase-compensated signal to produce a fine carrier phase estimate.

30           The invention further provides a carrier phase recovery system for use in a multiple-link hopping and burst adaptive modem in steady state operation. In one

embodiment, the carrier phase recovery system includes a memory and a fixed equalizer for equalizing a present data burst of a present link for which the tap coefficients pertinent to a previous burst. The carrier phase unit includes a first stage which acquires a coarse estimate of the carrier phase offset using a pilot-aided technique using multiple known pilot symbols contained in the present burst of data, a fixed phase bias removal stage coupled to the first stage and a phasor generating stage coupled to the fixed phase bias removal stage. The carrier phase unit further includes a de-rotating means for de-rotating the filtered (equalized) signal by a phasor signal generated by the phasor generating stage to remove estimated coarse carrier phase from the filtered signal to produce a coarse phase-compensated signal. The carrier phase unit further includes a data-aided phase estimator stage for removing modulated signal from the coarse phase-compensated signal using a data-aided, decision-directed technique, an averaging means for averaging N symbols from the data-aided phase estimator stage to reduce noise variance, and an equalizer stage for generating the tap coefficients and storing the tap coefficients in the memory.

The foregoing discussion of the preferred embodiments has been provided only by way of introduction. Nothing in this section should be taken as a limitation on the following claims, which define the scope of the invention.

## BRIEF DESCRIPTION OF SEVERAL VIEWS OF THE DRAWINGS

FIG. 1 is a block diagram of a link hopping wireless network having a mesh topology;

FIG. 2 shows a general block diagram of a prior art maximum likelihood (ML) carrier phase recovery system;

FIG. 3 illustrates frame construction of a transmitted burst in the wireless network of FIG. 1;

FIG. 4 is a block diagram of a carrier phase synchronization system for use in a node of the wireless network of FIG. 1 in burst-mode operation;

FIG. 5 is a detailed block diagram of a carrier phase recovery unit for burst-mode operation of the wireless network of FIG. 1;

FIG. 6 shows the frame structure of transmitted burst for pilot acquisition in a pilot-aided acquisition unit employed in the joining process for the wireless network of FIG. 1; and

FIG. 7 is a detailed block diagram of a carrier phase recovery unit for the joining process of the wireless network of FIG. 1.

#### DETAILED DESCRIPTION OF THE PRESENTLY PREFERRED EMBODIMENTS

This invention relates to the carrier phase recovery subsystem for a link-hopping wireless mesh network topology used for Broadband Wireless Access (BWA) networks. Such networks operate in different spectra such as in the Local Multi-point Distributed Service (LMDS) band at 28 GHz. The modem of a node in such a network is capable of fast link-hopping from one link to another over slow time-varying channels. That is, the channel is quasi-static from burst to burst for any given link. A carrier phase estimation technique is provided for a coherent detection of high-speed short-burst multi-link hopping mesh network topology using, for example, fixed Broadband Wireless Access (BWA).

Fading in fixed line-of-sight (LOS) channels, although mild compared to mobile systems, provides disruptive effects for phase tracking. The use of closed-loop systems, such as phase-locked loops or modified Costas phase trackers, is not appropriate for burst modem applications. In these environments, closed-loop systems typically fail to provide improved performance due to their large cycle-slip rate in fading channels and/or slow convergence rate in short-burst broadband applications.

The present embodiments are designed to enhance performance as compared to non-coherent M-ary modulation schemes through employing fast and efficient algorithms, while maintaining low-implementation complexity and high-throughput efficiency. A pilot-aided coherent phase estimation technique along with a decision-directed scheme are the scope of this embodiment for extracting the carrier phase of the transmitted signal in a time-varying channel environment involving a dynamic mesh networks employing high-speed, short-burst data.



To achieve coherent detection in a short-burst and high-speed mesh infrastructure, reliable carrier phase recovery must be performed. In principle, non-aided schemes alone are most efficient, however, their performance becomes critical even for a very robust modulation signaling (i.e., B/QPSK) when operating in low signal-to-noise ratio (SNR) and/or the channel is impaired by fading.

In the burst mode, the carrier phase recovery unit of the present embodiments conducts a multiple-stage phase recovery scheme. First, the received signal is matched filtered and is passed through a fixed T/N-spaced equalizer to compensate for the phase and amplitude variations of the link under the operation. When a new burst of a particular link is received in the mesh topology (multi-point to multi-point), the weights of the fixed equalizer for that link are updated based on the tap coefficients of an equalizer which has operated on the previous burst of the corresponding link. In this embodiment, the tap coefficients of the fixed equalizer are loaded from memory into a T/2-spaced equalizer. That is, in the present embodiments, each node has N sets of tap coefficients stored in its local memory corresponding to its N neighboring nodes.

The present embodiments provide a novel and improved method and system for carrier phase recovery. The estimation of carrier phase is conducted in two distinct modes. The first mode is the join mode where a new node is invited to join a mesh radio system. In this mode, the carrier phase is estimated through a long sequence of known, un-modulated, pilot symbols.

In the second mode, the carrier phase is estimated when the mesh infrastructure is in a burst or steady-state operation. The focus of this discussion is primarily on this mode of the carrier phase estimation. Although there are a number of traditional closed-loop phase recovery techniques (i.e., PLL, Costas loop, etc.) available and cited in the literature, the present embodiments utilizes a novel multi-stage open-loop structure to efficiently operate with a burst modem within the existing mesh network capable of link hopping on a burst by burst basis.

FIG. 1 is a block diagram of an exemplary wireless radio network 100 employing a mesh topology. The network 100 as illustrated in FIG.1 includes a first node 102, a second node 104, a third node 106 and a fourth node 108 in radio

communication. The network 100 may include any number of nodes. The four nodes shown in FIG. 1 are exemplary only. In the embodiment of FIG. 1, the network 100 is a wireless mesh topology network of the type described in US Patent Application serial number 09/187,665, entitled "Broadband Wireless Mesh Topology Networks" and filed November 5, 1998 in the names of J. Berger and I. Aaronson.

Each node 102, 104, 106, 108 includes data processing apparatus and a radio for communication of data with remote radios, such as other nodes of the network 100. Each node in the exemplary embodiment includes a directional antenna that provides radio communication on a number of sectors. The sectors provide radio coverage over a portion of the geographic area near a node. Thus, node 104 includes sectors 112 providing coverage over an area 116 which includes node 102. Node 102 provides coverage over an area 114. Node 106 provides coverage over an area 118, and node 108 provides coverage over an area 120.

Nodes 102, 104, 106, 108 of the network 100 are considered peers. They are free to communicate with one another on an equal basis. This is in distinction to a hierarchical system such as base stations communicating with subscriber units in a cellular radiotelephone system. Communication among the nodes 102, 104, 106, 108 is peer-to-peer communication.

Two nodes are in radio communication when their antenna sectors align. In that case, the nodes may complete a radio link and exchange data and control information. Thus, node 102 and node 104 communicate on link 128, node 102 and node 108 communicate on link 126, and node 104 and node 108 communicate on a link 134.

The fixed broadband wireless network 100 operates in two modes. A first mode is referred to as the acquisition/join mode. A second mode is referred to as the steady-state or burst mode. Operation will be described in greater detail below in conjunction with FIGS. 3-5. In the first mode of operation, the present invention obtains an accurate estimate of the carrier phase through averaging the estimated phase of K inserted pilot symbols into the designated slot of the join packet. In one embodiment, K=32. The join process will be described in greater

detail below in conjunction with FIGS. 6 and 7. The join process may be of the type described in U.S. Patent Application serial number 09/699,582 entitled "Join Process Method For Admitting A Node To A Wireless Mesh Network, filed October 30, 2000 in the names of Y. Kagan, et al.

5 In the exemplary embodiment of FIG. 1, node 106 may be considered a joining node which is in the process of joining the network 100 including existing nodes 102, 104, 108. The joining node 106 receives invitation packets from the existing nodes 102, 104, 108 and can thus establish radio communication with node 102 on a link 130 with node 103 and on a link 132 with node 108.

10 FIG. 2 is a block diagram of a prior art maximum likelihood carrier phase recovery system 200. FIG. 2 illustrates a generic block diagram of a Maximum Likelihood (ML) phase estimator. The parameter  $\hat{f}$  is the frequency offset,  $\hat{\tau}$  represents the timing phase,  $\{\hat{d}(m)\}$  are the information symbols,  $g(k)$  is the square-root raised-cosine matched filter (signaling pulse shape),  $T$  is the symbol period, and  $\hat{\theta}$  is the carrier phase to be estimated.

15 All parameters,  $\hat{f}$ ,  $\hat{\tau}$ ,  $\{\hat{d}(m)\}$ , and the pulse-shaping filter,  $g(k)$ , are assumed to be known to the receiver. The phase  $\hat{\theta}$  is the only unknown constant, taking values in the range of  $\pm \pi$ . The knowledge of the data symbols may come from either a decision-directed scheme or a known preamble (pilot symbols). The symbol epoch and carrier frequency values are estimated in advance and  
20 independently of carrier phase and are accurately tracked between bursts.

The system 200 illustrates the operations necessary to recover the carrier phase in a radio receiver of the system 100. The system 200 is an idealized or canonical representation. Actual embodiments of a system which can accomplish  
25 the illustrated operations requires an accurate and efficient estimate of  $\{\hat{d}(m)\}$  within the context a multi-hopping link system. Forming an effective and efficient embodiment is particularly compounded in the present system where short bursts comprising the pilot signal of only two symbols are implemented for system efficiency reasons.

The carrier phase recovery system 200 includes a mixer 202, a filter 204, a sampler 206, a multiplier 208, a summer 210 and an angle determination block 212. The system 200 receives a signal  $r(k)$  which includes received data samples. The filter 204 is a matched filter having a filter response  $g(-k)$  which matches to the transmitter pulse shaping filter  $g(k)$ .

The sampler 206 samples the output signal every  $T$  seconds, producing the signal  $x(k)$  which has a timing phase shift equal to  $\hat{\tau}$ . The multiplier 208 multiplies the signal  $x(k)$  by the signal  $\{\hat{d}^*\}$  which is a known signal or known data, or an estimate thereof. In the present embodiment,  $\hat{d}^*$  is a known pilot signal in the first stage of the carrier phase recovery system and an estimate of an unknown data in the second stage, respectively. The product signal which is provided to the summer 210. The multiplier 208 de-rotates the received signal. The summer 210 averages symbols over a time period corresponding to an observational window of interest. The angle determination block 212 extracts the angle associated with the data and produces an angle  $\hat{\theta}$ . This angle corresponds to the phase offset or phase error of the received data.

As noted above, the system 200 of FIG. 2 is a canonical form for estimation of carrier phase. However, in the system of FIG. 1, radio signals are received as short bursts including short (e.g., two-symbol) pilot signals. Also, the system of FIG. 1 is a link hopping system in which one radio signal is received on a frequency during certain receive times. The receive times may be interspersed with times during which other signals are received. The embodiments illustrated below relate to a system and method for recovering carrier phase in a link-hopping, burst-mode radio receiver.

FIG. 3 illustrates a frame format of a transmitted burst 300 in the wireless network 100 of FIG. 1. The burst 300 is of the type used for on-going, burst mode communication among nodes of the network 100 and is distinct from a burst used in the join process to be described below in conjunction with FIG. 6. The burst 300 is one example of a data burst. As is shown in FIG. 3, the burst 300 includes data symbols and known pilot symbols 304 at a known timing position inside the

data burst. Two pilot symbols are used in the illustrated embodiment, but any suitable number could be used. The pilot symbols are inserted between data symbols of the packet data burst 300. The packet may contain any suitable number of symbols. In the illustrated embodiment,  $m$  is the number of data symbols per packet and is chosen to be 32. This frame structure embeds the pilot symbols in the data for reliable phase estimation and data recovery.

The present embodiments include a carrier phase estimation unit which includes a fixed equalizer to compensate for the phase and amplitude variations of individual links capable of operating on multiple links independently, a pilot-symbol-based estimation apparatus to produce a coarse estimate of the value of the carrier phase, a decision-directed phase recovery method to provide the estimates of the symbol data in order to remove the modulating signals, and an averaging and phase extraction means to generate the final phase estimate.

The combination of a fixed equalizer, pilot-based coarse phase estimation, decision-directed data estimator, a smoothing filter, and a phase extractor means over  $M$  symbols which are all implemented in an open loop (feed-forward) structure brings about improvements in carrier phase tracking capability and provides an accuracy which is very close to the Modified Cramer-Rao bound ( $\text{MCRB}(\theta)$ ). The individual aspects of the present embodiments each provide respective system and performance enhancements when used alone or in conjunction with either prior art designs or disclosed elements.

FIG. 4 is a block diagram of a carrier phase synchronization system 400 for use in a node of the wireless network of FIG. 1 in burst mode operation. The system 400 forms an overall carrier phase recovery system. The system 400 may be implemented in a radio receiver which receives a modulated signal as a series of bursts of data on a plurality of links in a link hopping radio communication system such as the system 100 of FIG. 1. In particular embodiments, each burst may include one or more pilot symbols and data symbols. In one embodiment, the radio receiver including the system 400 operates in the local multipoint distribution service (LMDS) band at 28 GHz on a channel that is slowly changing

with time. The radio receiver receives broadcasts of quadrature amplitude modulated (QAM) data. The radio receiver hops among a plurality of radio links to receive bursts of radio signals on the plurality of radio links. Depending on the configuration of the particular network, the bursts received at the receiver on a particular channel from a particular transmitter may be interleaved with bursts from other transmitters on other channels. Applications with other systems having other operational features are possible, as well.

In this exemplary embodiment, each burst of data may have the format illustrated in FIG. 3. The pilot symbols are chosen to be at maximum amplitude corners of the QAM constellation. As shown in FIG. 3, in the time domain, the pilot symbols may be located near the center of the burst, which is, for example, 32 symbols in duration. The carrier phase synchronization system 400 of FIG. 4 uses the inserted pilot symbols and the estimated data symbols to accurately recover the carrier phase offset for the short bursts.

The system 400 includes a delay element 402, a mixer or multiplier 404 and an adaptive equalizer 406. The system further includes a non-adaptive equalizer 408, a carrier phase recovery unit 410 which recovers phase for the present burst of data using pilot and data symbols, and a memory circuit 412. Upon receipt of an initial burst (signal i1 in FIG. 4) at an input 420, the burst or symbols of the burst is delayed in the delay block 402. The delayed data (signal i6 in FIG. 4) on line 421 are multiplied in the multiplier by a carrier phase estimate (signal i5 in FIG. 4) on line 426 from the carrier phase recovery unit 410. The multiplier or mixer 404 combines a delayed present burst of data and the recovered phase estimate to produce a phase-error compensated signal (signal z1 in FIG. 4) on the line 428. Structure and operation of the carrier phase recovery unit 410 will be described in more detail below in conjunction with FIG. 5.

The output signal z1 from the multiplier 404 is provided on line 428. The signal is provided to the adaptive equalizer 406 which compensates for phase and amplitude variations of the channel. The equalizer 406 produces an equalized output signal (signal i7 in FIG. 4) and provides next burst equalizer weights to the fixed equalizer 408 for equalizing a next burst of data. In the illustrated

embodiment, the next burst equalizer weights are stored in memory 412 but separate storage may be omitted. The equalizer 406 performs a T/N-spaced adaptive equalization process and an equalized and carrier phase error compensated signal is produced at the output 422. As part of the adaptive equalization process, equalizer weights are produced by the adaptive equalizer 406. These equalizer weights correspond to the particular link from which received radio signals are currently processed. The adaptive equalizer 406 compensates for amplitude and carrier phase variations in the channel and/or provides appropriate channel side information for each radio link from the received burst on the radio link. Other techniques of characterizing the channel or link may be used instead of or in addition to determining equalizer weights or carrier phase.

The equalizer weights, channel phase or other determined channel information are stored in the memory 412. In the illustrated embodiment, the memory 412 is a random access memory. In alternative embodiments, other storage devices may be substituted. In a link-hopping network embodiment, such as the network 100 of FIG. 1, the equalizer weights are preferably stored in accordance with an indication of the link with which they are associated. In this manner, in response to a select signal received at an input of the memory 430, the equalizer weights may be retrieved (signal i3 in FIG. 4) from the memory 412 for use in equalization of a subsequent burst. When each subsequent burst for a particular link is received, the adaptive equalizer 406 updates the equalizer weights for the next received burst using the current equalizer weights or other determined channel information from a received burst. The adaptive equalizer 406 then stores the updated equalizer weights in the memory 412.

The equalizer 408 receives the stored equalizer weights as signal i3 from the memory 412. As noted, in a multiple-link or link-hopping system, the stored equalizer weights are preferably retrieved from the memory according to the link to be received. The equalizer 408 uses the equalizer weights or other determined channel information for the radio link to reliably receive a next received burst on the radio link. That is, when the next burst for that particular link is received, the

SELECT signal is asserted at the input 430 to the memory 412 to retrieve the equalizer weights previously stored for the link. The equalizer 408 produces an equalized signal using the retrieved equalizer weights. The equalized signal is provided to the carrier phase recovery unit 410 on a line 424.

FIG. 4 illustrates the top-level block diagram of the carrier phase estimator unit according to one embodiment in which a carrier phase synchronizer and a fixed or non-adaptive equalizer 408 preceding the phase estimator 410 are combined. The non-adaptive equalizer 408 pre-compensates for the phase and amplitude variations of the received symbols of the  $j$ -th burst of the  $l$ -th link,  $l = 1, \dots, N$  (where  $N$  is the number of neighbors associated with any given node.) The tap coefficients of the fixed equalizer 408 are the same as the tap coefficients of an adaptive equalizer employed after the carrier phase recovery unit 410 operated on the  $j - 1$ -st (previous) burst of the  $l$ -th link.

In the preferred embodiment, the carrier phase recovery unit 410 provides the carrier phase estimates of every  $j$ -th burst of all  $N$  neighboring links,  $\{\hat{\theta}(j, l) | l = 1, \dots, N\}$ , independently. The carrier phase recovery means is employed in one application in a multi-hopping link topology such as a mesh architecture. All elements of the present invention are preferably constructed in a digital system.

The transmitted signal, channel multiplicative distortion, and the additive white Gaussian noise corresponding to the  $j$ -th burst of the  $l$ -th link at the sampling instant  $i$  are denoted by the complex signals  $s(i, j, l)$ ,  $c(i, j, l) = \alpha(i, j, l)e^{j\phi(i, j, l)}$  and  $n(i, j, l)$ , respectively. Then, the received symbols for the  $l$ -th link is defined as:

$$r(i, j, l) = c(i, j, l) \cdot s(i, j, l) + n(i, j, l) \quad 1)$$

The received complex signals are assumed to be carrier frequency offset compensated, matched filtered, and the timing phase parameter is accurately



estimated, before being processed through a fixed (non-adaptive) fractionally-spaced equalizer and carrier phase recovery means as described above.

In the steady-state (burst) operation of the carrier phase estimator unit, the received signal,  $i1$ , is first filtered through a fixed T/2-spaced equalizer 408 (FIG. 4) to compensate for any phase and amplitude variations experienced in the slowly-varying fading environment. The tap coefficients of the fixed equalizer 408 are provided by the adaptive T/2-spaced equalizer 406 operated on the previous burst of the current link. We denote the tap coefficients of the adaptive equalizer 406 by  $\{w(k,j,l); k=1,\dots,L; l=1,\dots,N\}$ , where  $w(k,j,l)$  is the  $k$ -th tap coefficient of the  $j$ -th burst of the  $l$ -th link. The parameters,  $L$ , maximum number of tap coefficients, and  $N$ , maximum number of existing neighbors of the target receiver (inviting node) are the design parameters and hence variable.

At the end of each  $j$ -th burst of the  $l$ -th link, the tap coefficients,  $w(k,j,l)$ , are stored in the memory 412. These tap coefficients are loaded into the fixed equalizer 408 for pre-compensating the phase and amplitude variations of the next ( $j+1$ -st) burst, assuming the channel is slowly changing from burst to burst for a given  $l$ -th link. The pre-compensated phase and amplitude of the complex signal is inputted to the carrier phase recovery unit where,

$$i2(i,j,l) = \sum_{k=1}^L w(k,j-1,l) \cdot i1(i-k,j,l) \quad \text{for } l=1,\dots,N \quad 2)$$

Note that in the preceding notation, the index  $i$  is used interchangeably for either the  $i$ -th symbol position within the  $j$ -th burst or the sampling time, assuming that one sample per symbol processing is considered.

The delay block 402 in FIG. 4 is provided to account for all processing delays encountered in the fixed equalizer 408 and the carrier phase recovery unit 410, respectively.

In the present embodiment of the carrier phase estimation unit 410 in the steady-state (burst) mode, the multiplexed  $p$  pilot symbols of the  $l$ -th link are

represented by  $\{P(1,l), P(2,l), \dots, P(p,l)\}$ . For the carrier phase recovery system, only two opposite corners of the designated M-QAM (i.e.,  $M = 4, 16, 64$  or  $256$ ) constellation points are used as defined by:

$$\begin{aligned} P(i,l) &= r(i,l)e^{j\theta(i,l)}, \\ P(i-1,l) &= r(i-1,l)e^{j\theta(i-1,l)} \end{aligned} \quad 3)$$

where  $r(i,l) = r(i-1,l)$  and  $\theta(i,l) = -\theta(i-1,l) = \pi/4$ .

In a multiple link environment, the system 400 may receive bursts over several independent channels from different receivers. At some times, the system 400 may receive multiple bursts or a continuous transmission from a single transmitter. In the general case, though, the system 400 receives one burst from one transmitter on a first channel and subsequently, a second burst from the same transmitter on the same first channel. Bursts from one or more other transmitters are interspersed between the first and second bursts on the channel.

The system 400 thus receives a first burst of a first radio signal on a first radio link. For example, in FIG. 1, the node 102, which includes the system 400 in this example, may receive a burst on link 126 from node 108. The system 400 determines channel information, such as the carrier phase, about the first radio link using the first burst. The system 400 stores the equalizer weights, carrier phase or other channel information. The system 400 then receives a first burst of a second radio signal on a second radio link, such as the link 128 in FIG. 1. The system 400 determines channel information about the second radio link using the first burst of the second radio signal. The channel information for the second radio link is stored. Subsequently, the system 400 receives a next burst of the first radio signal on the first radio link, such as link 126 in FIG. 1, using the equalizer weights or other channel information.

One embodiment of the carrier phase recovery unit 410 is shown in greater detail in FIG. 5. FIG. 5 represents the details of carrier phase recovery unit in burst mode according to one embodiment. After the amplitude and phase

variations of the received burst are compensated (minimized) through the fixed  $T/2$ -spaced equalizer for the  $l$ -th link (FIG. 4), a coarse estimate of the carrier phase,  $\hat{\theta}(j,l)$ , is obtained based on the  $p$  pilot symbols in the  $j$ -th burst of the  $l$ -th link,  $\{P(1,j,l), \dots, P(p,j,l)\}$ . These known symbols are multiplexed periodically with the data symbols as shown in FIG. 3. Depending on the number of pilots inserted and the periodicity ( $T_p = p + m$ ,  $p$  pilots for every  $m$  data symbols,  $m \gg p$ ), conventional techniques known in prior art such as linear interpolation, low-pass filter interpolation, or Gaussian interpolation can be applied to obtain the estimates of the channel parameters.

In the preferred embodiment, the estimation of the phase and amplitude variations of the I/Q components of the available pilot symbols can be performed. The value of the amplitude information of a multiplicative distortion obtained by this method can also be used to enhance the precision of automatic gain control (AGC).

Another added advantage of these periodic pilot symbols is to reduce the impact of the phase noise. This benefit can be readily realized by performing a new estimate of the carrier phase (using the available  $p$  pilot symbols) every  $m$  data symbols. That is, after every  $m$  data symbols, a new estimate of the carrier phase could be provided. In this case, the phase estimate,  $\hat{\theta}$ , is updated every  $p + m$  symbols. These independent carrier phase estimates could be very instrumental to relax the impact of phase noise particularly in high-level QAM modulation schemes. Since the loop bandwidth of the feed-forward carrier phase recovery technique is inversely proportional to the period of the integration or estimation length of the observed symbols, it is desirable to increase the periodicity of the inserted pilots or equivalently to reduce the parameter,  $T_p$ . The pilot sequence period ( $T_p$ ) is a design parameter which should be set based on a trade-off metric between the desired phase noise reduction and the throughput efficiency.

The carrier phase recovery unit 410 uses a pilot based and decision aided algorithm for phase estimation. The signal to be received is a series of bursts, each burst having a number of pilot symbols, preferably located near the center of then shortest burst. The carrier phase recovery unit 410 provides carrier phase recovery in burst mode applications.

The burst-mode of the carrier phase recovery unit 410 relies on a coarse estimate of the carrier phase utilizing  $p$  pilot symbols multiplexed with the data in the transmitted burst. In this embodiment, two opposite corner symbols (i.e.,  $p = 2$ ) of the M-QAM constellation are assigned as pilot symbols. The current embodiment inserts these two known symbols adjacent to one another in the middle of the data stream in a pre-assigned time slot.

In a preferred embodiment, the pilot symbols can be used for estimation of multiplicative amplitude distortion of a fading channel. Pilot symbol assisted modulation (PSAM) is an alternative to a transparent time-in-band (TTIB) method. The periodically inserted pilot symbols are interpolated to generate the estimates of time-varying channel parameters such as phase and amplitude distortions. These pilot symbols can be used to reduce the impact of the phase noise.

In order that the variations of amplitude and phase caused by the modulation of a carrier, the modulation must be removed. Such variations are from the distortions by the fading channel and other residual impairments caused by the radio transceiver. After the phase of the burst is de-rotated by a coarse estimate of the carrier phase, the modulating data of the information-bearing symbols are removed through a decision-directed phase recovery apparatus. The fine measurement of the phase is now carried out over these  $M$  symbols. The resulting unmodulated symbols are processed through a non-causal averaging unit to smooth out the carrier phase estimate of the first  $M$  symbols of the burst. The parameter  $M$  is selected based on the burst length and the channel condition. In the embodiment described herein, a value of  $M=32$  is used. Other values could be used in other designs. This smoothing process, improves the accuracy of the

estimated phase value significantly and enhances the reliability of the phase estimate through reducing the impact of the additive white Gaussian noise.

In the embodiment of FIG. 5, a two-stage phase recovery technique is used on each burst. Thus, the carrier phase recovery unit 410 includes a coarse carrier phase estimation circuit 502 and a fine carrier phase estimation circuit 504 to produce the recovered phase. The coarse carrier phase estimation circuit 502 is configured to produce a coarse estimate of the phase for the present burst of data using the pilot symbols of the present burst of data. The fine carrier phase estimation circuit 504 is coupled to the coarse carrier phase estimation circuit to produce the recovered phase using the coarse estimate of the phase and at least some of the data contained in the burst.

FIG. 5 illustrates the detailed block diagram of the carrier phase recovery unit 410 employed in a burst mode. After the received signal is phase and amplitude compensated by the fixed equalizer the pilot symbols, p1 and p2 are demultiplexed by the block 506 and processed to obtain a coarse estimate of the carrier phase. First, the pilot symbols located at the symbol positions  $i$  and  $i-1$  (i.e., 17th and 16th) of the current ( $j$ -th) burst of the  $l$ -th link are extracted. These two pilot symbols are then subtracted from each other by summer 508 to generate a complex signal:

$$z4(j,l) = p(i,l) - p(i-1,l) = 2\alpha(i,l) \cdot r(i,l)e^{j(\phi(i,l)+\pi/4)} + n(i,l) - n(i-1,l) \quad 4)$$

where the preceding operation is done only once per burst. The indices  $j$  and  $l$  correspond to the  $j$ -th burst of the  $l$ -th link of the mesh network, respectively.

The phase of the complex signal,  $z4$ , is subsequently extracted using conventional techniques such as the known CORDIC scheme by CORDIC algorithm block 510. The summer 512 removes the residual phase bias value,  $\pi/4$  in Equation 4), from the phase argument,  $z5$ , to produce a coarse estimate of the undesired phase distortion,  $\hat{\phi}(j,l)$ . The impact of the additive white Gaussian noise and any residual phase impairment from the circuit components are also

reflected in the undesired phase estimate  $\hat{\phi}(j,l)$ . A complex signal,  $z9 = e^{-j\hat{\phi}(j,l)}$ , is formed through using known techniques such as a look-up table unit 514 and a complex conjugate converter 516.

The pre-compensated complex signal is delayed by the delay block 520 to account for the processing delays encountered in the pilot-aided carrier phase recovery conducted in the previous stage. The complex delayed signal is now multiplied by the signal  $z9$  in the multiplier 522 to counter-rotate the phase by the coarse phase estimate,  $\hat{\phi}(j,l)$ . The resulting complex signal,  $z11$ , already refined by the fixed equalizer and phase compensated by the aid of the pilot symbol means, are now provided to the slicer 524. The complex signal  $z11$  is denoted by:

$$z11(i,j,l) = s(i,j,l) \cdot \alpha(i,j,l) e^{j[\theta(i,j,l) + \phi_e(i,j,l)]} + n(i,j,l) \quad (5)$$

and  $se^{j\theta}$  is the transmitted desired data. The residual undesired phase,  $\phi_e$ ,

$$\phi_e(i,j,l) = \phi(i,l) - \hat{\phi}(j,l) \quad (6)$$

is now reduced in magnitude and helps the slicer 524 to have negligible decision errors as described below.

In the next stage, a data-aided phase recovery scheme is used to remove the data-dependent phase portion of the received signal. In the previous stage, the undesired phase was estimated per burst for all  $N$  links based on the known pilot symbols. In this stage, the unknown data symbols of the entire burst or a portion of the burst are first estimated through a QAM slicer 524. The estimated phase of the data symbols is removed from the output of the fixed equalizer. At the input to the slicer 524, the complex signal has the form specified by equation 1). However, the channel parameters are pre-compensated by the aid of the fixed equalizer and the pilot-based stage of the carrier phase recovery unit.

At the output of the slicer 524, the estimated data symbols,  $\hat{s}(i, j, l)e^{j\hat{\theta}(i, j, l)}$ , are removed from the complex signal z11. The resulting complex signal would be:

$$z14 = s(i, j, l) \cdot \hat{s}^*(i, j, l) \cdot \alpha(i, j, l) e^{j[\theta(i, j, l) - \hat{\theta}(i, j, l) + \phi_e(i, j, l)]} = s^2(i, j, l) \cdot \alpha(i, j, l) e^{j\phi_e(i, j, l)} \quad 7)$$

5

In equation 7), it is assumed that the detector has committed no errors and the impact of Gaussian noise is negligible.

The complex signal, z14, is averaged over  $M$  symbols and the phase is extracted using the CORDIC algorithm in the CORDIC algorithm block 534 analogous to the process described in the pilot-aided scheme, namely:

10

$$z15(j, l) = \sum_{i=0}^{M-1} z14(i, j, l) = \sum_{i=0}^{M-1} s^2(i, j, l) \cdot \alpha(i, j, l) e^{j\phi_e(i, j, l)} \quad 8)$$

$$\angle z15(j, l) = z17 = \Phi(j, l) \quad 9)$$

15

Note that each estimated carrier phase,  $\Phi(j, l)$ , of the  $j$ -th burst of the  $l$ -th link is independently calculated and is fixed for the entire  $j$ -th burst. The complex signal  $z15 = e^{-j\Phi(j, l)}$  at the output 426 is formed using the table look up block 536 and complex conjugate block 538.

20

Referring again to FIG. 4, the received signal from the input 420 is delayed in delay block 402 and phase compensated in the multiplier 404 by the estimated carrier phase,  $\Phi(j, l)$ , to generate the complex signal z1 (ignoring the impact of the delay element 402) on line 428, where

25

$$z1(i, j, l) = z15(i, j, l) \cdot e^{-j\Phi(j, l)} = [s(i, j, l) \cdot \alpha(i, j, l)] e^{j\{\theta(i, j, l) + \phi_e(i, j, l) - \Phi(j, l)\}} \quad 10)$$

The signal,  $z_1$ , is further processed by an adaptive T/2-spaced equalizer 406 to compensate the amplitude and phase variation of the channel,  $\alpha(i, j, l)e^{j\phi(i, j, l)}$ . The resulting output signal,  $i7$ , at the output 422, is denoted as:

$$i7(i, j, l) = \sum_{k=1}^L w(k, j, l) \cdot z_1(i-k, j, l) \quad \text{for } l=1, \dots, N \quad (11)$$

where the tap coefficients,  $\{w(k, j, l), k=1, \dots, L\}$ , of the  $j$ -th burst of the  $l$ -th link are stored in the memory 430. These coefficients are uploaded into the fixed T/2-spaced equalizer 408 to pre-compensate the phase and amplitude variations of the next ( $j+1$ -st) burst of the  $l$ -th link.

The burst-mode of the carrier phase recovery unit relies on a coarse estimate of the carrier phase utilizing  $p$  pilot symbols multiplexed with the data in the transmitted burst. In this invention, two opposite corner symbols (i.e.,  $p=2$ ) of the M-QAM constellation are assigned as pilot symbols. The current embodiment inserts these two known symbols adjacent to one another in the middle of the data stream in a pre-assigned time slot.

The coarse carrier phase estimation circuit 502 performs a pilot-aided carrier phase estimation. The coarse carrier phase estimation circuit 502 thus includes a pilot extraction block 506, a summer 508, a CORDIC algorithm block 510, a summer 512, a look up table block 514 and a complex conjugate block 516. The coarse carrier phase estimation circuit 502 estimates phase using the pilot symbols embedded in the burst.

The coarse carrier phase estimation circuit 502 is coupled to the equalizer 408 to receive the initial equalized input signal on line 424 from the equalizer 408 (FIG. 4). This signal is provided to the pilot extraction block 506 which locates the pilot symbols at a predetermined location in the burst. In the illustrated example, the pilot symbols are located near the center of the (short) burst. However, the pilot symbols may be located at any appropriate location, either together or separate, within the burst. In the illustrated example, the pilot



extraction block 506 buffers all 32 samples of the (short) burst. The sixteenth and seventeenth samples are then selected as the pilot symbols  $P_1$  and  $P_2$ . The extracted pilot symbols  $P_1$  and  $P_2$  are subtracted in the summer 508. The results of the subtraction are provided to the CORDIC algorithm block 510. The CORDIC algorithm is known in the art and useful for evaluating the inverse tangent of the input argument to obtain the phase of the subtracted corner points of the QAM constellation at  $\pi/4$  radians. A fixed value of  $\pi/4$  is subtracted from the output signal of the CORDIC algorithm block 510 to remove the  $\pi/4$  bias from the pilots which are at the corners of the M-QAM constellation and produce an estimate of the phase angle. A table lookup operation is performed on the signal 26 in the block 514 to obtain sine and cosine values to form a complex phasor corresponding to the estimated phase angle. A complex conjugate operation is performed in the complex conjugate block 516 which is inputted to the fine carrier estimation block 504.

The fine carrier phase estimation circuit 504 extracts a data-aided carrier phase estimation. The fine carrier phase estimation circuit 504 includes a delay element 520, a multiplier 522, a QAM slicer 524, a complex conjugate block 526, a multiplier 528, a summer 530, a delay element 532, a CORDIC algorithm block 534, a table look up block 536 and a complex conjugate block 538. The delay element 520 is coupled to the equalizer 408 (FIG. 4) to receive the initial equalized input signal on line 424 from the equalizer 408 (FIG. 4). The delay element 520 delays the received signal during processing in the coarse carrier phase estimation circuit 502.

The multiplier 522 multiplies the delayed signal from the delay element 520 and the coarse carrier phase estimate. The multiplier 522 operates as a de-rotating circuit to receive an initial equalized signal to remove estimated coarse carrier phase from the initial equalized signal responsive to an estimate signal from the coarse carrier phase estimation signal. The signal from the complex conjugate circuit 516 is in the form of a complex phasor. The residual phase error, after the de-rotating circuit, is now much less in magnitude and helps the detector/slicer 524 to have negligible decision errors.

The de-rotator output signal is provided to the slicer 524. The slicer 524 makes a decision as to the symbol of the received signal.

The complex conjugate of the estimated transmitted data is evaluated in the complex conjugate block 526, which operates similarly to the complex conjugate block 516 of the coarse carrier phase estimation circuit 502. The result is multiplied by the received, equalized signal on line 424 in the multiplier 528 to remove the estimated phase of the data symbols from the fixed equalizer output. This signal is provided to the summer 530.

In the feedback loop including the delay element 532, the values are averaged over a predetermined number of data symbols. In different embodiments, the averaging occurs over some or all data symbols in a burst. In one example, a window of data symbols of a received burst is averaged. Averaging a predetermined number of symbols of the carrier estimate to reduce noise variance.

The inverse tangent is evaluated in the CORDIC algorithm block 534 to obtain an estimate of the phase angle. The sine and cosine are evaluated in the look up table block 536 and the complex conjugate is again evaluated, yielding the fine estimate of the carrier phase. The receiver circuit including the system 400 may subsequently process the received radio signals, such as correcting carrier phase for the radio signal using the fine estimation of carrier phase.

FIG. 6 shows the frame structure 600 of a transmitted burst for pilot acquisition in a joining process for the wireless network 100 of FIG. 1. In the join mode,  $K$  known pilot symbols dedicated for the carrier phase estimation are multiplexed with other training sequences in the transmitted join frame as shown in FIG. 6

In the joining process, a new or joining node is added to an existing network of one or more nodes. For example, in the exemplary embodiment shown in FIG. 1, if node 106 is a joining node which is joining the network 100 which already includes node 102, 104, 108, node 106 must locate radio signals from other nodes in the network 100, including locating direction and frequency of the radio signals. Further, the node 106 must acquire timing synchronization with the

other nodes using the radio signals. Still further, the joining node 106 must initiate communication with one or more existing nodes so that its presence can be recorded in the network.

In the embodiment of FIG. 6, a frame structure 600 for a transmitted burst includes all pilot symbols 602. The frame 600 is of duration K pilot symbols, where K may be any selected number. Transmitting only pilot symbols simplifies the joining process at the joining receiver. However, in alternative embodiments, other frame structures including other data content may be substituted. The frame structure 600 thus forms an invitation burst having data symbols and known pilot symbols at a known timing position inside the invitation burst.

In conjunction with the system shown in FIG. 4, the frame structure 600 may be used to fill the memory 412 with initial stored channel information. That is, the first burst generally received by the system 400 in a joining node wishing to join the network is an invitation burst as illustrated in FIG. 6. After equalization by the adaptive T/N spaced equalizer 406, the equalizer weights are stored in the memory. The equalizer weights form link parameters for the new radio link from an established node in the network to the joining node. The link parameters or equalizer weights are stored as initial channel information. Upon receipt of subsequent bursts, the link parameters may be updated. If either another invitation burst or a data burst is received from the established node on the new radio link, the stored channel information may be updated with new equalizer weights which reflect variation in the channel.

FIG. 7 is a block diagram of a carrier phase recovery unit 700 for use in the joining process to add a new node to the wireless network 100 of FIG. 1. The carrier phase recovery unit 700 includes a summer 702, a delay element 704, a CORDIC algorithm block 706, a look up table block 708 and a complex conjugate block 710. The carrier phase recovery unit 700 receives an equalized input signal  $y_1$  at the input 712. The input signal in one embodiment has the frame structure shown in FIG. 6. That is, the input signal consists of all pilot symbols. The feedback loop including the summer 702 and the delay element 704 operates to average the received symbols over a window of samples.

The inverse tangent is evaluated in the CORDIC algorithm block 706 to obtain an estimate of the carrier phase angle. The sine and cosine are evaluated in the look up table block 708 and the complex conjugate is evaluated in the complex conjugate block 710, yielding an estimate of the carrier phase for the pilot symbol transmission. The receiver circuit including the system 700 may subsequently process the received radio signals, such as correcting carrier phase for the radio signal using the fine estimation of carrier phase.

The pilot symbols,  $r(i,l)e^{j\theta(i,l)}$ , are extracted and averaged over  $K$  symbols to produce the estimated phase,  $\Phi(l)$  as shown in FIG. 7:

$$y3(l) = \sum_{i=0}^{K-1} y1(i,l) = \sum_{i=0}^{K-1} r(i,l) \cdot \alpha(i,l) e^{j\varphi(i,l)} \quad (12)$$

$$\angle y3(l) = y4(l) = \Phi(l) \quad (13)$$

where the indices  $i$  and  $l$  denote the  $i$ -th pilot symbol position and the  $l$ -th link of a mesh network, respectively.

Finally, the incoming complex signal is counter-rotated by the estimated phase,  $\Phi(l)$ , to compensate for the undesired phase induced by the channel and other phase impairment introduced in the transceiver radio.

From the foregoing, it can be seen that the present embodiments provide a method and apparatus for carrier phase recovery in a burst mode system. Information about the radio link, such as equalizer weights appropriate for the link, is stored for subsequent use in a receiver. For carrier phase recovery, first a coarse estimate is made of carrier phase using pilot symbols of the received data. The coarse estimated is then used for making a fine estimate in a data-directed carrier phase recovery technique.

While a particular embodiment of the present invention has been shown and described, modifications may be made. The operational blocks shown in the block diagrams of the drawing may be embodied as hardware components, software code operating in conjunction with hardware, or a combination of the

two. Implementation of such functions in hardware, software or a combination thereof is well within the purview of those ordinarily skilled in the appropriate art. Further, such illustrated functionality may be combined with other operations by way of modification. Accordingly, it is therefore intended in the appended claims to cover such changes and modifications which follow in the true spirit and scope of the invention.

5

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2